



Список схем и условия их приобретения - <http://www.chat.ru/~micar>
List schemes and conditions of the sale - <http://schematics.bizland.com>

Regulator

ICW (TAPPOBA)									
PIN NO.	PLAY	STOP	F.F	REW	P.WD. S	REV. S	JET P.WD. S	JET REV. S	STILL
PIN 1	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5
PIN 2	2.5	2.5	2.5	2.5	2.5	2.4	2.5	2.5	2.4
PIN 3	0	4.4	0	0	0	0	0	0	4.4
PIN 4	3.5	3.5	3.5	0	3.5	0	3.5	0	3.5
PIN 5	0	0	0	0	0	0	0	0	0
PIN 6	0	0	0	0	0	0	0	0	0
PIN 7	0	4.8	4.8	0	0	0	0	0	0
PIN 8	0	0	0	0	0	0	0	0	5.1
PIN 9	0	0	5.0	5.0	5.0	5.0	0	0	0
PIN 10	0	0	0	0	0	0	4.7	4.7	0
PIN 11	0	4.5	4.5	0	0	0	0	0	0
PIN 12	0	0	0	0	5.0	5.0	5.0	5.0	5.0
PIN 13	1.4	0	1.3	1.5	1.4	1.3	1.4	1.4	1.4
PIN 14	1.5	5.2	1.3	1.3	1.3	1.3	1.4	1.4	1.4
PIN 15	1.3	0	1.4	1.3	1.4	1.3	1.4	1.4	1.4
PIN 16	1.4	0	1.4	1.3	1.4	1.3	1.4	1.4	1.4
PIN 17	3.8	3.8	1.2	0.5	1.1	0.5	1.2	0.5	1.2
PIN 18	0.5	3.7	3.7	3.8	0.5	0.5	0.5	0.5	3.7
PIN 19	3.7	3.7	0.5	1.4	0.5	1.2	0.5	1.3	1.2
PIN 20	3.7	3.7	1.1	1.3	1.1	1.2	1.2	1.3	1.2
PIN 21	0	0	0	0	0	0	0	0	0
PIN 22	0.5	3.6	0.5	0.5	0.5	0.5	0.5	0.5	0.5
PIN 23	-	-	-	-	-	-	-	-	-
PIN 24	0	0	0	0	0.1	0.2	0.2	0.2	0.2

[illegible]

FWD. S: FWD SEARCH
REV. S: REVERSE SEARCH

[illegible]

FWD. S: FWD SEARCH
REV. S: REVERSE SEARCH

MODE	PLAY			STOP			F.F			REW			FWD.S			REV.S			JET FWD.S			JET REV.S			STILL		
	E	B	C	E	B	C	E	B	C	E	B	C	E	B	C	E	B	C	E	B	C	E	B	C	E	B	C
Q701	1.3	2.2	0.1	1.5	2.2	0.1	1.5	2.3	0	1.3	2.3	0	1.3	2.2	0.2	1.3	2.2	0	1.4	2.3	0	1.3	2.2	0	1.4	2.2	0
Q702	0	0	2.1	0	0	2.1	0	0	2.2	0	0	2.7	0	0	2.2	0	0	2.1	0	0	2.2	0	0	2.2	0	0	2.2
Q703	0	0	2.1	0	0	2.1	0	0	2.2	0	0.7	2.5	0	0	2.2	0	0	2.1	0	0	2.2	0	0	2.1	0	0	2.2
Q707	0	0.1	5.9	0	0.1	5.9	0	0.1	5.9	0	0.1	5.9	0	0.2	5.9	0	0.2	5.9	0	0.2	5.9	0	0.2	5.9	0	0.2	5.9
Q708	5.1	5.9	5.2	5.1	5.9	5.2	5.1	5.9	5.2	5.1	5.9	5.2	5.1	5.9	5.2	5.1	5.9	5.2	5.1	5.9	5.2	5.1	5.9	5.2	5.1	5.9	5.2
Q709	0	0	5.8	0	0	5.8	0	0	4.3	0	0	4.3	0	0	5.8	0	0	5.8	0	0	5.8	0	0	5.8	0	0	5.8
Q710	5.1	5.8	5.1	0	0	5.2	0	0	5.2	0	0	5.2	5.1	5.8	5.1	5.1	5.8	5.1	5.1	5.8	5.1	5.1	5.8	5.1	5.1	5.8	5.1

